



High power contactor, TeSys Giga, 4 pole (4NO), AC-1 <=440V 250A, advanced version, 200...500V wide band AC/DC coil

LC1G1154LSEA

Main	
Range	TeSys
Range of product	TeSys Giga
Product or component type	Contactor
Device short name	LC1G
Contactor application	Power switching
Utilisation category	AC-1 AC-5a AC-5b AC-6a AC-6b DC-1 DC-3 DC-5
Poles description	4P
[Ue] rated operational voltage	<= 1000 V AC 50/60 Hz <= 460 V DC
[le] rated operational current	250 A (at <40 °C) at <= 1000 V AC-1
[Uc] control circuit voltage	200500 V AC 50/60 Hz 200500 V DC
Control circuit voltage limits	Operational: 0.8 Uc Min1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max0.45 Uc Min (at <60 °C)

## Complementary

- · · · · · · · · · · · · · · · · · · ·	
[Uimp] rated impulse withstand voltage	8 kV
Overvoltage category	Ш
[Ith] conventional free air thermal current	250 A (at 40 °C)
Rated breaking capacity	1040 A at 440 V
[Icw] rated short-time withstand current	1.1 kA - 10 s 0.64 kA - 30 s 0.52 kA - 1 min 0.4 kA - 3 min 0.32 kA - 10 min
Associated fuse rating	125 A aM at <= 440 V for motor 125 A aM at <= 690 V for motor 315 A gG at <= 690 V
Average impedance	0.00018 Ohm
[Ui] rated insulation voltage	1000 V

10 W AC-1 - Ith 250 A  LC1G 4 NO 1 NO + 1 NC
4 NO
1 NO + 1 NC
1560 A at 440 V
Built-in bidirectional peak limiting
5 Mcycles 8 Mcycles with sub-assembly substitution
295 VA
215 W
13.0 VA
8.0 W
4070 ms closing 1550 ms opening
300 cyc/h AC-1
Power circuit: bar 2 - busbar cross section: 25 x 6 mm  Power circuit: lugs-ring terminals 1 185 mm²  Power circuit: bolted connection  Control circuit: push-in 1 0.22.5 mm² - cable stiffness: solid stranded without cable end  Control circuit: push-in 1 0.252.5 mm² - cable stiffness: flexible with cable end  Control circuit: push-in 2 0.51.0 mm² with cable end  Control circuit: push-in 0.752.5 mm² - cable stiffness: solid stranded without cable end  Control circuit: push-in 0.752.5 mm² - cable stiffness: flexible with cable end
35 mm
Plate
EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1
313 C6201-3-1
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
CB Scheme CCC cULus EAC CE UKCA
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm  143 mm  193 mm  5.1 kg
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm  143 mm
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm  143 mm  193 mm  5.1 kg
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm  143 mm  193 mm  5.1 kg  IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106
CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  255 mm  143 mm  193 mm  5.1 kg  IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106  -2560 °C

Halogen free plastic parts product
Yes
End of Life Information
Product Environmental Profile
Yes
China RoHS declaration
Yes
Compliant EU RoHS Declaration
REACh Declaration
Green Premium product
35.496 kg
80.000 cm
60.000 cm
105.000 cm
4 405 000 cm
P06
6.374 kg
39.000 cm
26.700 cm
25.000 cm
1
PCE
-4070 Cat OC
TH -4070 °C at Uc

## **Product data sheet**

## LC1G1154LSEA

Installation

## **Installation Videos**

TeSys Giga - How to install the auxiliary contact block

TeSys Giga - How to install and remove remote wear diagnosis module

TeSys Giga - How to install mechanical interlock kit

TeSys Giga - How to replace control module

TeSys Giga - How to replace switching modules

TeSys Giga - How to assemble change-over solution

Recommended replacement(s)